

# TRY6

## P77/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill Lira 5, 10, 20, 50, 100, 200 6bills.

| FUNCTION                                    | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / 5 Lira                          | OFF | OFF | OFF |     |     |     |     |     |     |      |
| 2 Pulses / 5 Lira                           | OFF | OFF | ON  |     |     |     |     |     |     |      |
| 3 Pulses / 5 Lira                           | OFF | ON  | OFF |     |     |     |     |     |     |      |
| 4 Pulses / 5 Lira                           | OFF | ON  | ON  |     |     |     |     |     |     |      |
| 5 Pulses / 5 Lira                           | ON  | OFF | OFF |     |     |     |     |     |     |      |
| 10 Pulses / 5 Lira                          | ON  | OFF | ON  |     |     |     |     |     |     |      |
| 20 Pulses / 5 Lira                          | ON  | ON  | OFF |     |     |     |     |     |     |      |
| 100 Pulses / 5 Lira                         | ON  | ON  | ON  |     |     |     |     |     |     |      |
| Fast output Pulse<br>Lo= 50ms<br>Hi=100ms   |     |     |     | ON  |     |     |     |     |     |      |
| ★ Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
| Inhibit level Active Low                    |     |     |     |     | ON  |     |     |     |     |      |
| ★ Inhibit level Active High                 |     |     |     |     | OFF |     |     |     |     |      |
| ★ Accept 5 & 10 Lira                        |     |     |     |     |     | ON  |     |     |     |      |
| Reject 5 & 10 Lira                          |     |     |     |     |     | OFF |     |     |     |      |
| ★ Accept 20 Lira                            |     |     |     |     |     |     | ON  |     |     |      |
| Reject 20 Lira                              |     |     |     |     |     |     | OFF |     |     |      |
| ★ Accept 50 Lira                            |     |     |     |     |     |     |     | ON  |     |      |
| Reject 50 Lira                              |     |     |     |     |     |     |     | OFF |     |      |
| ★ Accept 100 Lira                           |     |     |     |     |     |     |     |     | ON  |      |
| Reject 100 Lira                             |     |     |     |     |     |     |     |     | OFF |      |
| ★ Accept 200 Lira                           |     |     |     |     |     |     |     |     |     | ON   |
| Reject 200 Lira                             |     |     |     |     |     |     |     |     |     | OFF  |

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

### Currency Assign Data

| Interface<br>Bill value | Pulse   | ccTalk  |
|-------------------------|---------|---------|
| BV1                     | 5 Lira  | 5 Lira  |
| BV2                     | 10 Lira | 10 Lira |
| BV3                     | 20 Lira | 20 Lira |
| BV4                     | 50 Lira | 50 Lira |

| Interface<br>Bill value | Pulse    | ccTalk   |
|-------------------------|----------|----------|
| BV5                     | 100 Lira | 100 Lira |
| BV6                     | 200 Lira | 200 Lira |

## P77-TRY6/P5(Pulse/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse)

| FUNCTION            | SW1 | SW2 | SW3 | SW4 |
|---------------------|-----|-----|-----|-----|
| ★ Pulse Normal High | ON  |     |     |     |
| Pulse Normal Low    | OFF |     |     |     |
| ★ Pulse Protocol    |     | ON  |     |     |
| ccTalk Protocol     |     | OFF |     |     |
| Harness Disable     |     |     | ON  |     |
| ★ Harness Enable    |     |     | OFF |     |
| Manufacture Default |     |     |     | ON  |
| ★ System Default    |     |     |     | OFF |

★ Manufacture setting

Note: (1) Dip switches 1 & 3 are only used for pulse protocol.

### DIP SWITCHES SETTING : 2(ccTalk)

| FUNCTION                 | SW1 | SW2 | SW3 | SW4 |
|--------------------------|-----|-----|-----|-----|
| ★ Encryption Mode        | ON  |     |     |     |
| Decrypt Mode             | OFF |     |     |     |
| Pulse Protocol           |     | ON  |     |     |
| ★ ccTalk Protocol        |     | OFF |     |     |
| ccTalk Parameters Reset  |     |     | ON  |     |
| ★ Keep ccTalk Parameters |     |     | OFF |     |
| Manufacture Default      |     |     |     | ON  |
| ★ System Default         |     |     |     | OFF |

(★) Manufacture setting

Note:(1) ccTalk Parameters Reset

Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

\*This has to be done after finished calibration process.