

## V7-CLP5

### V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill Ch\$ 1000, 2000, 5000, 10000, 20000 5bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Ch\$ 1000	ON											
★ Accept Ch\$ 1000	OFF											
★ Reject Ch\$ 2000		ON										
★ Accept Ch\$ 2000		OFF										
★ Reject Ch\$ 5000			ON									
★ Accept Ch\$ 5000			OFF									
★ Reject Ch\$ 10000				ON								
★ Accept Ch\$ 10000				OFF								
★ Reject Ch\$ 20000					ON							
★ Accept Ch\$ 20000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 Pulse / Ch\$ 1000									OFF	OFF		
2 Pulses / Ch\$ 1000									ON	OFF		
4 Pulses / Ch\$ 1000									OFF	ON		
20 Pulses / Ch\$ 1000									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

## V7-CLP5(Pulse/ICT004/MDB)

### V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
★ Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

### Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	Ch\$ 1000	Ch\$ 1000	Ch\$ 1000
BV2	Ch\$ 2000	Ch\$ 2000	Ch\$ 2000
BV3	Ch\$ 5000	Ch\$ 5000	Ch\$ 5000
BV4	Ch\$ 10000	Ch\$ 10000	Ch\$ 10000
BV5	Ch\$ 20000	Ch\$ 20000	Ch\$ 20000