

NK77F-THB5

NK77F DIP SWITCHES SETTING : (Pulse/Out of Service/ICT104U/ICT10A/ccTalk)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

DIP SWITCHES SETTING : (Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF								
	2 Pulse / THB 10	OFF	ON								
	5 Pulse / THB 10	ON	OFF								
	10 Pulse / THB 10	ON	ON								
★	Enable Fish Stop			ON							
	Disable Fish Stop			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
★	Accept THB 500 & 1000					ON					
	Reject THB 500 & 1000					OFF					
★	Enable Output Sensor Detect						ON				
	Disable Output Sensor Detect						OFF				
★	Pluse Normal High						ON				
	Pluse Normal Low						OFF				
	Pulse Mode							ON		ON	
	ICT104U Mode								OFF	ON	
	ICT10A Mode								ON	OFF	
	CCTALK Mode								OFF	OFF	

(★) Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ICT10A	CCTALK
BV1	THB 20	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000	THB 1000

NK77F -THB5(Pulse/Out of Service/ICT104U/ICT10A/ccTalk)

DIP SWITCHES SETTING : (ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Encryption MODE (Nota.2)	ON									
	Decrypt MODE (Nota.2)	OFF									
	CCTalk Parameters Restore Switch		ON								
★	Please see Note,3 for Detail		OFF								
★	Enable Fish Stop			ON							
	Disable Fish Stop			OFF							
	8-bit checksum				ON						
★	CRC 16-bit checksum				OFF						
★	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
★	Accept THB 500 & 1000					ON					
	Reject THB 500 & 1000					OFF					
	Enable Output Sensor Detect							ON			
★	Disable Output Sensor Detect							OFF			
★	Pluse Normal High								ON		
	Pluse Normal Low								OFF		
	Pulse Mode									ON	ON
	ICT104U Mode									OFF	ON
	ICT10A Mode									ON	OFF
	CCTALK Mode									OFF	OFF

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) The function is valid when the Dip4 is OFF(CCTALK).

(3) Turn this dip to with restart the bill acceptor will restore CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) Pulse mode has out of service function.

(5) Out of service:Normal High,Error Low.

(6) Pulse speed is LO=50ms/HI=100ms.