

XBA mini-KWD4

XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill KWD 0.25, 0.5, 1, 5 4bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4		
Reject KWD 0.25	ON													
Accept KWD 0.25	OFF													
Reject KWD 0.5		ON												
Accept KWD 0.5		OFF												
Reject KWD 1			ON											
Accept KWD 1			OFF											
Reject KWD 5				ON										
Accept KWD 5				OFF										
Reserved													ON	
Reserved													OFF	
Disable Bill Reject 4 Times BA Stop By 30 Sec													ON	
Enable Bill Reject 4 Times BA Stop By 30 Sec													OFF	
Stack Banknote when Power-up													ON	
Reject Banknote when Power-up													OFF	
Reserved													ON	
Reserved													OFF	
Inhibit Active High													ON	
Inhibit Active Low													OFF	
Reserved													ON	
Reserved													OFF	
Interface Timing Conversion	50ms LO / 50ms HI												OFF	OFF
	60ms LO / 300ms HI												ON	OFF
	30ms LO / 50ms HI												OFF	ON
	150ms LO / 150ms HI												ON	ON

★ Manufacture setting

After setting dip switch of the credit pulses,you should reset the bill acceptor again.
Note :1. Calibration card is needed.

XBA mini-KWD4(Pulse/MDB/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / KWD 0.25			OFF	OFF
2 pulses / KWD 0.25			OFF	ON
4 pulses / KWD 0.25			ON	OFF
20 pulses / KWD 0.25			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT JPSTD converter board	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface	ICT104U	ICT104V	Pulse	MDB
Bill value				
BV1	KWD 0.25	KWD 0.25	KWD 0.25	KWD 0.25
BV2	KWD 0.5	KWD 0.5	KWD 0.5	KWD 0.5
BV3	KWD 1	KWD 1	KWD 1	KWD 1
BV4	KWD 5	KWD 5	KWD 5	KWD 5

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 3	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(Other)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting