

L70+/L70F-NAD10(NAD7+ZAR3)

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ccTalk)

Supported bill NAD 10, 20, 30, 50, 60, 100, 200 7bills.
ZAR 50, 100, 200 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / NAD10 & ZAR10	OFF	OFF	OFF							
2 Pulses / NAD10 & ZAR10	OFF	OFF	ON							
3 Pulses / NAD10 & ZAR10	OFF	ON	OFF							
4 Pulses / NAD10 & ZAR10	OFF	ON	ON							
5 Pulses / NAD10 & ZAR10	ON	OFF	OFF							
10 Pulses / NAD10 & ZAR10	ON	OFF	ON							
20 Pulses / NAD10 & ZAR10	ON	ON	OFF							
100 Pulses / NAD10 & ZAR10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept NAD 10 & 20 & 30 & 60						ON				
Reject NAD 10 & 20 & 30 & 60						OFF				
★ Accept NAD 50 & ZAR 50							ON			
Reject NAD 50 & ZAR 50							OFF			
★ Accept NAD 100 & ZAR 100								ON		
Reject NAD 100 & ZAR 100								OFF		
★ Accept NAD 200 & ZAR 200									ON	
Reject NAD 200 & ZAR 200									OFF	
Accept NAD ONLY										ON
★ Accept NAD and ZAR										OFF

★ Manufacture Default setting

Note 1. Please reset the bill acceptor after any changes on Dip switch.

2. Dip Switch 1 to 5 are only for Pulse mode.

3. Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L70+/L70F-NAD10(NAD7+ZAR3)(Pulse/ICT104U/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
ICT104U Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★ ICT104U Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

Decrypt MODE

FUNCTION	SW1	SW2	SW3	SW4
8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
Pulse Mode		ON	OFF	
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
ICT104U Interface		ON	ON	
★ Encryption Mode				ON
Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

	8-bit	CRC 16-bit
Encryption MODE	Reserved	ON
Decrypt MODE	Reserved	OFF

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	NAD 10	NAD 10	NAD 10
BV2	NAD 20	NAD 20	NAD 20
BV3	NAD 50	NAD 50	NAD 50
BV4	NAD 100	NAD 100	NAD 100
BV5	NAD 200	NAD 200	NAD 200
BV6	NAD 30	NAD 30	NAD 30
BV7	NAD 60	NAD 60	NAD 60
BV8	ZAR 50	ZAR 50	ZAR 50
BV9	ZAR 100	ZAR 100	ZAR 100
BV10	ZAR 200	ZAR 200	ZAR 200