

V6-MXN2

V6 Option Switch Settings : 1

Supported bill MXN 20, 50 2bills.

V6 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MXP 20	ON											
★	Accept MXP 20	OFF											
★	Reject MXP 50		ON										
★	Accept MXP 50		OFF										
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / MXN 10									OFF	OFF		
	2 pulse / MXN 10									ON	OFF		
	5 pulse / MXN 10									OFF	ON		
	10 pulse / MXN 10									ON	ON		
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

◆ Factory configuration has all switches in the OFF position.

V6-MUN2

V6 Interface Settings: 2(M.D.B)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Reserved		ON		
★	M.D.B Interface		OFF		
★	Reserved			ON	
★				OFF	
★					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB
BV1	20
BV2	50