

BR2300-AOA4

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill AOA 200, 500, 1000, 2000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject AOA 200 & 500	ON									
	Accept AOA 200 & 500	OFF									
★	Reject AOA 1000		ON								
	Accept AOA 1000		OFF								
★	Reject AOA 2000			ON							
	Accept AOA 2000			OFF							
★	High Acceptance (Note.3)				ON						
	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)				ON						
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				OFF						
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk							ON	OFF		
	ccTalk (Note.1)							OFF	ON		
★	MDB Mode							OFF	OFF		
★	ICT-BC Mode							ON	ON		
	ccTalk	MDB Mode			ICT-BC Mode						
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)			Connect with MDB Connector						ON
	Decrypt MODE	Standard MDB Recycler Function			★ Connect with RS232 Connector						OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1	AOA 200	AOA 200	AOA 200
BV2	AOA 500	AOA 500	AOA 500
BV3	AOA 1000	AOA 1000	AOA 1000
BV4	AOA 2000	AOA 2000	AOA 2000