

## BR2300-CLP5

### BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill CLP 1000, 2000, 5000, 10000, 20000 5 bills.

|   | FUNCTION                                                               | SW1                                      | SW2 | SW3 | SW4 | SW5                            | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|------------------------------------------------------------------------|------------------------------------------|-----|-----|-----|--------------------------------|-----|-----|-----|-----|------|
| ★ | Reject CLP 1000 & 2000                                                 | ON                                       |     |     |     |                                |     |     |     |     |      |
|   | Accept CLP 1000 & 2000                                                 | OFF                                      |     |     |     |                                |     |     |     |     |      |
| ★ | Reject CLP 5000 & 10000                                                |                                          | ON  |     |     |                                |     |     |     |     |      |
|   | Accept CLP 5000 & 10000                                                |                                          | OFF |     |     |                                |     |     |     |     |      |
| ★ | Reject CLP 20000                                                       |                                          |     | ON  |     |                                |     |     |     |     |      |
|   | Accept CLP 20000                                                       |                                          |     | OFF |     |                                |     |     |     |     |      |
| ★ | High Acceptance (Note.3)                                               |                                          |     |     | ON  |                                |     |     |     |     |      |
|   | High Security                                                          |                                          |     |     | OFF |                                |     |     |     |     |      |
| ★ | Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0 (MDB Only) |                                          |     |     |     | ON                             |     |     |     |     |      |
|   | Scaling Factor (SF) = 10<br>Decimal Point Position (DPP) = 1           |                                          |     |     |     | OFF                            |     |     |     |     |      |
| ★ | Normal                                                                 |                                          |     |     |     |                                | OFF | OFF |     |     |      |
|   | Load Banknote to Recycle                                               |                                          |     |     |     |                                | ON  | OFF |     |     |      |
|   | Load Banknote to Stacker                                               |                                          |     |     |     |                                | OFF | ON  |     |     |      |
|   | Unload Banknote to Stacker                                             |                                          |     |     |     |                                | ON  | ON  |     |     |      |
| ★ | ccTalk                                                                 |                                          |     |     |     |                                |     |     | ON  | OFF |      |
|   | ccTalk (Note.1)                                                        |                                          |     |     |     |                                |     |     | OFF | ON  |      |
| ★ | MDB Mode                                                               |                                          |     |     |     |                                |     |     | OFF | OFF |      |
| ★ | ICT-BC Mode                                                            |                                          |     |     |     |                                |     |     | ON  | ON  |      |
|   | ccTalk                                                                 | MDB Mode                                 |     |     |     | ICT-BC Mode                    |     |     |     |     |      |
|   | ★ Encryption MODE                                                      | ★ Virtual MDB Recycler Function (Note.2) |     |     |     | Connect with MDB Connector     |     |     |     | ON  |      |
|   | Decrypt MODE                                                           | Standard MDB Recycler Function           |     |     |     | ★ Connect with RS232 Connector |     |     |     | OFF |      |

#### ★ Manufacture setting

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.4: Calibration card is needed.

### Currency Assign Data

| Interface<br>Bill value | ccTalk    | ICT-BC    | MDB       | Recycler banknote inventory |        |
|-------------------------|-----------|-----------|-----------|-----------------------------|--------|
| BV1                     | CLP 1000  | CLP 1000  | CLP 1000  | CLP 1000                    | 45 pcs |
| BV2                     | CLP 2000  | CLP 2000  | CLP 2000  | CLP 2000                    | 45 pcs |
| BV3                     | CLP 5000  | CLP 5000  | CLP 5000  | CLP 5000                    | 45 pcs |
| BV4                     | CLP 10000 | CLP 10000 | CLP 10000 | CLP 10000                   | 40 pcs |
| BV5                     | CLP 20000 | CLP 20000 | CLP 20000 | CLP 20000                   | 40 pcs |