

BR2300-COP7

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject COP 1000 & 2000 & 5000	ON									
★	Accept COP 1000 & 2000 & 5000	OFF									
★	Reject COP 10000 & 20000 & 50000		ON								
★	Accept COP 10000 & 20000 & 50000		OFF								
★	Reject COP 100000			ON							
★	Accept COP 100000			OFF							
★	High Acceptance (Note.3)			ON							
★	High Security			OFF							
★	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	(MDB Only)				ON					
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk							ON	OFF		
	ccTalk (Note.1)							OFF	ON		
★	MDB Mode							OFF	OFF		
★	ICT-BC Mode							ON	ON		
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

★ Manufacture setting

- Note.1. Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.
2. Recycled Banknote represents as a virtualMDB coin type.
3. High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.
4. Calibration card is needed.

BR2300-COP7(MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	MDB	ICT-BC	Recycler banknote inventory	
BV1	COP 1000	COP 1000	COP 1000	COP 1000	45 pcs
BV2	COP 2000	COP 2000	COP 2000	COP 2000	45 pcs
BV3	COP 5000	COP 5000	COP 5000	COP 5000	45 pcs
BV4	COP 10000	COP 10000	COP 10000	COP 10000	45 pcs
BV5	COP 20000	COP 20000	COP 20000	COP 20000	45 pcs
BV6	COP 50000	COP 50000	COP 50000	COP 50000	40 pcs
BV7	COP100000	COP100000	COP100000	COP100000	40 pcs