

BR2300-LAK8

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/MDB Dummy)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject LAK 500 & 1000 & 2000	ON									
	Accept LAK 500 & 1000 & 2000	OFF									
	Reject LAK 5000 & 10000 & 20000		ON								
★	Accept LAK 5000 & 10000 & 20000		OFF								
	Reject LAK 50000 & 100000			ON							
★	Accept LAK 50000 & 100000			OFF							
	High Acceptance (Note.2)				ON						
★	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB Only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
★	MDB Dummy								ON	OFF	
★	ICT-BC Mode								ON	ON	
★	MDB Mode								OFF	OFF	
★	Reserved								OFF	ON	
	MDB Dummy Mode	MDB Mode			ICT-BC Mode						
	No Refund After the Deal	Virtual MDB Recycler Function (Note.1)			Connect with MDB Connector						ON
★	Refund After the Deal	★ Standard MDB Recycler Function			★ Connect with RS232 Connector						OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1 Recycled Banknote represents virtual MDB coin type.

Note.2: High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Note.3: calibrate card.

Currency Assign Data

Interface Bill value	MDB(Dummy)		ICT-BC		Recycler banknote inventory	
BV1	LAK	500	LAK	500	LAK	500 40 pcs
BV2	LAK	1000	LAK	1000	LAK	1000 40 pcs
BV3	LAK	2000	LAK	2000	LAK	2000 40 pcs
BV4	LAK	5000	LAK	5000	LAK	5000 40 pcs
BV5	LAK	10000	LAK	10000	LAK	10000 40 pcs
BV6	LAK	20000	LAK	20000	LAK	20000 40 pcs
BV7	LAK	50000	LAK	50000	LAK	50000 40 pcs
BV8	LAK	100000	LAK	100000	LAK	100000 40 pcs