

BR2300-RUB7

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill RUB 50, 100, 200, 500, 1000, 2000, 5000 7 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	Reject RUB 50 & 100 & 200	ON									
★	Accept RUB 50 & 100 & 200	OFF									
	Reject RUB 500 & 1000		ON								
★	Accept RUB 500 & 1000		OFF								
	Reject RUB 2000 & 5000			ON							
★	Accept RUB 2000 & 5000			OFF							
	High Acceptance (Note.3)			ON							
★	High Security			OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON					
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0			OFF							
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk								ON	OFF	
	ccTalk (Note.1)								OFF	ON	
★	MDB Mode								OFF	OFF	
★	ICT-BC Mode								ON	ON	
	ccTalk	MDB Mode				ICT-BC Mode					
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON	
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note. 1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note. 2: Recycled Banknote represents virtual MDB coin type.

Note. 3: High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor.

Note. 4: Calibration card is needed.

BR2300-RUB7 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	ccTalk	ICT-BC	MDB
BV1			
BV2	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000
BV6	RUB 5000	RUB 5000	RUB 5000
BV7	RUB 200	RUB 200	RUB 200
BV8	RUB 2000	RUB 2000	RUB 2000