

BR2300-TRY6

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill TRY 5, 10, 20, 50, 100, 200 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reject TRY 5 & 10	ON									
	Accept TRY 5 & 10	OFF									
	Reject TRY 20 & 50		ON								
★	Accept TRY 20 & 50		OFF								
	Reject TRY 100 & 200			ON							
★	Accept TRY 100 & 200			OFF							
	High Acceptance (Note.3)				ON						
★	High Security				OFF						
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)			ON						
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				OFF						
★	Normal					OFF	OFF				
	Load Banknote to Recycle					ON	OFF				
	Load Banknote to Stacker					OFF	ON				
	Unload Banknote to Stacker					ON	ON				
★	ccTalk							ON	OFF		
	ccTalk (Note.1)							OFF	ON		
★	MDB Mode							OFF	OFF		
★	ICT-BC Mode							ON	ON		
	ccTalk	MDB Mode			ICT-BC Mode						
★	Encryption MODE	Virtual MDB Recycler Function (Note.2)			Connect with MDB Connector				ON		
	Decrypt MODE	Standard MDB Recycler Function			Connect with RS232 Connector				OFF		

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: High acceptance mode will increase accepting rate, however, it will reduce the security level of Bill Acceptor

Note.4: Calibration card is needed

Currency Assign Data

Interface Bill value	ccTALK	ICT-BC	MDB	Recycler banknote inventory	
BV1	TRY 5	TRY 5	TRY 5	TRY 5	45 pcs
BV2	TRY 10	TRY 10	TRY 10	TRY 10	45 pcs
BV3	TRY 20	TRY 20	TRY 20	TRY 20	45 pcs
BV4	TRY 50	TRY 50	TRY 50	TRY 50	40 pcs
BV5	TRY 100	TRY 100	TRY 100	TRY 100	40 pcs
BV6	TRY 200	TRY 200	TRY 200	TRY 200	40 pcs