

BR2300-VND9

BR2300 DIP SWITCHES SETTING : (ICT-BC)

Supported bill VND 1000, 2000, 5000, 10000, 20000

50000, 100000, 200000, 500000 9 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	Reject VND 1000 & 2000	ON									
★	Accept VND 1000 & 2000	OFF									
	Reject VND 5000 & 10000 & 20000 & 50000		ON								
★	Accept VND 5000 & 10000 & 20000 & 50000		OFF								
	Reject VND 100000 & 200000 & 500000			ON							
★	Accept VND 100000 & 200000 & 500000			OFF							
	High Acceptance				ON						
★	High Security				OFF						
	Reserved					ON					
★	Reserved					OFF					
★	Normal						OFF	OFF			
	Load Banknote to Recycle						ON	OFF			
	Load Banknote to Stacker						OFF	ON			
	Unload Banknote to Stacker						ON	ON			
	Reserved								ON	OFF	
	Reserved								OFF	ON	
	Reserved								OFF	OFF	
★	ICT-BC								ON	ON	
	Connect with MDB Connector										ON
★	Connect with RS232 Connector										OFF

★ Manufacture setting

After setting dip switch of the credit pulses,
you should reset the bill acceptor again.

Note.1: calibrate card.

Note.2: High acceptance mode will increasing
accepting rate, however, it will reduce
the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	ICT-BC	Interface Bill value	ICT-BC
BV1	VND 1000	BV6	VND 50000
BV2	VND 2000	BV7	VND 100000
BV3	VND 5000	BV8	VND 200000
BV4	VND 10000	BV9	VND 500000
BV5	VND 20000		