

BRV-COP7

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Col\$ 1000	ON											
★ Accept Col\$ 1000	OFF											
★ Reject Col\$ 2000 & 5000		ON										
★ Accept Col\$ 2000 & 5000		OFF										
★ Reject Col\$ 10000			ON									
★ Accept Col\$ 10000			OFF									
★ Reject Col\$ 20000				ON								
★ Accept Col\$ 20000				OFF								
★ Reject Col\$ 50000 & 100000					ON							
★ Accept Col\$ 50000 & 100000					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to Stacker						ON	ON					
Reserved								ON				
★ Reserved								OFF				
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved					6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibration card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

(5) JPSTD Dummy Mode credit divide by1000.

BRV-COP7(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
★ Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
★ Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode	(Note.5)		OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	Col\$ 1000	Col\$ 1000	Col\$ 1000	Col\$ 1000	35 pcs
BV2	Col\$ 2000	Col\$ 2000	Col\$ 2000	Col\$ 2000	35 pcs
BV3	Col\$ 5000	Col\$ 5000	Col\$ 5000	Col\$ 5000	35 pcs
BV4	Col\$ 10000	Col\$ 10000	Col\$ 10000	Col\$ 10000	35 pcs
BV5	Col\$ 20000	Col\$ 20000	Col\$ 20000	Col\$ 20000	35 pcs
BV6	Col\$ 50000	Col\$ 50000	Col\$ 50000	Col\$ 50000	30 pcs
BV7	Col\$ 100000	Col\$ 100000	Col\$ 100000	Col\$ 100000	30 pcs