

BRV-PHP6

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject PHP 20	ON											
★ Accept PHP 20	OFF											
Reject PHP 50		ON										
★ Accept PHP 50		OFF										
Reject PHP 100			ON									
★ Accept PHP 100			OFF									
Reject PHP 200				ON								
★ Accept PHP 200				OFF								
Reject PHP 500 & 1000					ON							
★ Accept PHP 500 & 1000					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to Stacker						ON	ON					
Reserved								ON				
★ Reserved								OFF				
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
Reserved			ON		5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved			OFF		6 Bank Note Limitation Per Transaction	ON	OFF	ON				
Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal						ON	
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibration card is needed.

(4) Recycked Banknote represents virtual MDB coin type.

BRV-PHP6(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	PHP 20	PHP 20	PHP 20	PHP 20	30 pcs
BV2	PHP 50	PHP 50	PHP 50	PHP 50	30 pcs
BV3	PHP 100	PHP 100	PHP 100	PHP 100	30 pcs
BV4	PHP 200	PHP 200	PHP 200	PHP 200	30 pcs
BV5	PHP 500	PHP 500	PHP 500	PHP 500	30 pcs
BV6	PHP 1000	PHP 1000	PHP 1000	PHP 1000	30 pcs