

# BRV-PUN5(PEN3+USD2)

## BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill PEN 10, 20, 50 3bills. USD 1, 5 2bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject PEN 10	ON											
★ Accept PEN 10	OFF											
★ Reject PEN 20		ON										
★ Accept PEN 20		OFF										
★ Reject PEN 50			ON									
★ Accept PEN 50			OFF									
★ Reject USD 1 (Note.3)				ON								
★ Accept USD 1 (Note.3)				OFF								
★ Reject USD 5 (Note.3)					ON							
★ Accept USD 5 (Note.3)					OFF							
★ Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to Stacker						ON	ON					
Reserved								ON				
★ Reserved								OFF				
<b>MDB Mode</b>	SW1	SW2	SW3	SW4	<b>JPSTD Dummy Mode</b>							
Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved				ON	5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
Reserved				OFF	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function				ON	No Refund After the Deal							ON
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

- (2) Please reset the bill acceptor after set the dip switch.
- (3) Exchange Rate on USD to PEN is 1:3 for MDB Mode)
- (4) Calibrate card.
- (5) Recycked Banknote represents virtual MDB coin type.

# BRV-PUN5(PEN3+USD2)(ICT-BC/MDB/JPSTD Dummy)

## Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

## Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB
BV1	PEN 10	PEN 10	PEN 10
BV2	PEN 20	PEN 20	PEN 20
BV3	PEN 50	PEN 50	PEN 50
BV4	USD 1	USD 1	USD 1
BV5	USD 5	USD 5	USD 5