

BRV-VND9

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000, 100000, 200000, 500000 9bills.

BRV dip-switch settings and functions:

FUNCTION													SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject VND 1000 & 2000 (Note,3)	ON																						
	Accept VND 1000 & 2000 (Note,3)	OFF																						
★	Reject VND 5000 & 10000		ON																					
	Accept VND 5000 & 10000		OFF																					
★	Reject VND 20000 & 50000				ON																			
	Accept VND 20000 & 50000				OFF																			
★	Reject VND 100000 & 200000 & 500000					ON																		
	Accept VND 100000 & 200000 & 500000					OFF																		
★	Standard Anti-Fish Security						ON																	
	High Anti-Fish Security						OFF																	
★	Normal								OFF	OFF														
	Load Banknote to Recycle								ON	OFF														
★	Disable Recycler Funtion								OFF	ON														
	Unload Banknote to Stacker								ON	ON														
★	High Acceptance (Note,5)								ON															
	Standard Acceptance								OFF															
★	MDB Mode	MDB Dummy Mode			SW1	SW2	SW3	SW4	JPSTD Dummy Mode															
	Reserved	Reserved			ON				★ 255 Bank Note Limitation Per Transaction	ON				ON	ON									
★	Reserved	Reserved			OFF				1 Bank Note Limitation Per Transaction	OFF				OFF	OFF									
	Reserved	Reserved				ON			2 Bank Note Limitation Per Transaction	ON				OFF	OFF									
★	Reserved	Reserved				OFF			3 Bank Note Limitation Per Transaction	OFF				ON	OFF									
	Reserved	Reserved							4 Bank Note Limitation Per Transaction	ON				ON	OFF									
★	Reserved	Reserved					ON		5 Bank Note Limitation Per Transaction	OFF				OFF	ON									
	Reserved	Reserved					OFF		6 Bank Note Limitation Per Transaction	ON				OFF	ON									
★	Reserved	Reserved						OFF	7 Bank Note Limitation Per Transaction	OFF				ON	ON									
	Virtual MDB Recycler Function (Note,6)	No Refund After the Deal						ON	No Refund After the Deal													ON		
★	Standard MDB Recycler Function	★ Refund After the Deal						OFF	★ Refund After the Deal													OFF		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) MDB Mode:

When Dip 1 is OFF,Reject VND 500000.

When Dip 1 is ON,Accept VND 500000.

(4) Calibration card is needed.

(5) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(6) Recycled Banknote represents virtual MDB coin type.

(7) Normal:Scaling Factor (SF) = 1 : Decimal Point Position (DPP) = 0

(8) The function(credit divide by1000) is used at standard MDB recycler mode.

(9) The function(credit divide by100) is used at standard MDB recycler mode.

Appendix

BRV-VND9(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
★	Reserved	ON			
★	Reserved	OFF			
★	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
★	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Normal Credit (Note.7)	OFF	OFF		
★	Credit divide by 1000 (Note.8)	OFF	ON		
★	Credit divide by 100 (Note.9)	ON	OFF		
★	Reserved	ON	ON		
★	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
★	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
★	No Bill Acceptor Error Code		ON		
★	Bill Acceptor Error Code		OFF		
★	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
★	Normal Credit (Note.7)	OFF	OFF		
★	Credit divide by 1000 (Note.8)	OFF	ON		
★	Credit divide by 100 (Note.9)	ON	OFF		
★	Reserved	ON	ON		
★	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB (Dummy)							
			When Dip 1 is OFF			When Dip 1 is ON				
			Note.7	Note.8	Note.9	Note.7	Note.8	Note.9	Recycler banknote inventory	
BV1	VND 1000	VND 1000	VND 1000	VND 1	VND 10	VND 5000	VND 5	VND 50	VND 1000	35 pcs
BV2	VND 2000	VND 2000	VND 2000	VND 2	VND 20	VND 10000	VND 10	VND 100	VND 2000	35 pcs
BV3	VND 5000	VND 5000	VND 5000	VND 5	VND 50	VND 20000	VND 20	VND 200	VND 5000	35 pcs
BV4	VND 10000	VND 10000	VND 10000	VND 10	VND 100	VND 50000	VND 50	VND 500	VND 10000	35 pcs
BV5	VND 20000	VND 20000	VND 20000	VND 20	VND 200	VND 100000	VND 100	VND 1000	VND 20000	35 pcs
BV6	VND 50000	VND 50000	VND 50000	VND 50	VND 500	VND 200000	VND 200	VND 2000	VND 50000	35 pcs
BV7	VND 100000	VND 100000	VND 100000	VND 100	VND 1000	VND 500000	VND 500	VND 5000	VND 100000	35 pcs
BV8	VND 200000	VND 200000	VND 200000	VND 200	VND 2000				VND 200000	30 pcs
BV9	VND 500000	VND 500000							VND 500000	30 pcs