

L70T-MMK6

L70T DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill K 100, 200, 500, 1000, 5000, 10000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / K 100	OFF	OFF	OFF								
	2 Pulses / K 100	OFF	OFF	ON								
	3 Pulses / K 100	OFF	ON	OFF								
	4 Pulses / K 100	OFF	ON	ON								
	5 Pulses / K 100	ON	OFF	OFF								
	10 Pulses / K 100	ON	OFF	ON								
	20 Pulses / K 100	ON	ON	OFF								
	100 Pulses / K 100	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms				ON							
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF							
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept K 100 & 200					ON						
	Reject K 100 & 200					OFF						
★	Accept K 500 & 1000						ON					
	Reject K 500 & 1000						OFF					
★	Accept K 5000							ON				
	Reject K 5000							OFF				
★	Accept K 10000									ON		
	Reject K 10000									OFF		
★	High Security										ON	
	High Acceptance (Nota3.)										OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	100	100	100
BV2	200	200	200
BV3	500	500	500
BV4	1000	1000	1000
BV5	5000	5000	5000
BV6	10000	10000	10000

Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.
 (3) High acceptance mode will increasing accepting rate,
 however, it will reduce the security level of Bill Acceptor.

L70T-MMK6(Pulse/RS232 A0/V2.2)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

RS232 A0 INFORMATION	
BillType Data	
Code	Denomination
1	K 100
2	K 200
3	K 500
4	K 1000
5	K 5000
6	K 10000
7	Reserved
8	Reserved
9	Reserved

DIP SWITCHES SETTING : 2(V2.2)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	RS232 A0 Mode		ON	ON	
★	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting