

## PL77&L77F-GBP1 (GBP+SCO+NOI)

### PL77-P3/P6 L77F-P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill

English banknotes: England £ 5

Scottish banknotes: Royal Bank & Bank of Scotland & Clydesdale Bank £ 5

Northern Ireland banknotes: £ 5

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / £ 5	OFF	OFF	OFF							
	2 Pulse / £ 5	OFF	OFF	ON							
	3 Pulse / £ 5	OFF	ON	OFF							
	4 Pulse / £ 5	OFF	ON	ON							
	5 Pulse / £ 5	ON	OFF	OFF							
	10 Pulse / £ 5	ON	OFF	ON							
	20 Pulse / £ 5	ON	ON	OFF							
	100 Pulse / £ 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept £ 5 (GBP)					ON					
	Reject £ 5 (GBP)					OFF					
★	Accept £ 5 (SCO)					ON					
	Reject £ 5 (SCO)					OFF					
★	Accept £ 5 (NOI)					ON					
	Reject £ 5 (NOI)					OFF					
★	Reserved									ON	
	Reserved									OFF	
★	Reserved										ON
	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## PL77-GBP1 P3/P6 L77F-GBP1 P2/P5 (Pulse/ICT/MDB)

### DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Interface Bill value	ICT	Pulse	MDB
BV1	£ 5 (GBP)	£ 5 (GBP)	£ 5 (GBP)
BV2	£ 5 (SCO)	£ 5 (SCO)	£ 5 (SCO)
BV3	£ 5 (NOI)	£ 5 (NOI)	£ 5 (NOI)

### DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100	ON			
	Decimal Point Position (DPP) = 2				
	Scaling Factor (SF) = 1	OFF			
	Decimal Point Position (DPP) = 0				
	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting