

L77F/PL77-BYR8

L77F/PL77-P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/Special MDB)

Supported bill Br 500, 1000, 5000, 10000, 20000, 5, 10, 20 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Br 500 Br 1000	OFF	OFF	OFF							
2 Pulses / Br 500 Br 1000	OFF	OFF	ON							
3 Pulses / Br 500 Br 1000	OFF	ON	OFF							
4 Pulses / Br 500 Br 1000	OFF	ON	ON							
5 Pulses / Br 500 Br 1000	ON	OFF	OFF							
10 Pulses / Br 500 Br 1000	ON	OFF	ON							
20 Pulses / Br 500 Br 1000	ON	ON	OFF							
100 Pulses / Br 500 Br 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Br 500 (Note.3)						ON				
Reject Br 500 (Note.3)						OFF				
★ Accept Br 1000 & 5000							ON			
Reject Br 1000 & 5000							OFF			
★ Accept Br 10000 & 20000								ON		
Reject Br 10000 & 20000								OFF		
★ Accept Br 5(2009) & 10(2009)									ON	
Reject Br 5(2009) & 10(2009)									OFF	
★ Accept Br 20(2009)										ON
Reject Br 20(2009)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switch 1 to 5 are only used for pulse protocol.

(3) When SW1 Dip 6 is ON

Pulse==>Br500=1 Pulse, Br1000=2 Pulse,Br5000=10 Pulse,Br10000=20 Pulse,Br20000=40 Pulse,
Br5(2009)=100 Pulse,Br10(2009)=200 Pulse,Br20(2009)=400 Pulse

MDB ==>Reject Br 20(2009).

When SW1 Dip 6 is OFF

Pulse==>Br1000=1 Pulse, Br5000=5 Pulse,Br10000=10 Pulse,Br20000=20 Pulse,Br5(2009)=50 Pulse,
Br10(2009)=100 Pulse,Br20(2009)=200 Pulse

MDB ==>Accept Br 20(2009).

L77F/PL77-BYR8 (Pulse/ICT104U/Special MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: MDB Mode Display :

Dip 6 OFF			Dip 6 ON		
Br 1000	=>	0.10	Br 500	=>	0.05
Br 5000	=>	0.50	Br 1000	=>	0.10
Br 10000	=>	1.00	Br 5000	=>	0.50
Br 20000	=>	2.00	Br 10000	=>	1.00
Br 5(2009)	=>	5.00	Br 20000	=>	2.00
Br 10(2009)	=>	10.00	Br 5(2009)	=>	5.00
Br 20(2009)	=>	20.00	Br 10(2009)	=>	10.00

Currency Assign Data

Dip 6 OFF			
Interface Bill value	ICT104U	Pulse	MDB
BV1			Br 1000
BV2	Br 1000	Br 1000	Br 5000
BV3	Br 5000	Br 5000	Br 10000
BV4	Br 10000	Br 10000	Br 20000
BV5	Br 20000	Br 20000	Br 5(2009)
BV6	Br 5(2009)	Br 5(2009)	Br 10(2009)
BV7	Br 10(2009)	Br 10(2009)	Br 20(2009)
BV8	Br 20(2009)	Br 20(2009)	

Currency Assign Data

Dip 6 ON			
Interface Bill value	Pulse	ICT104U	MDB
BV1	Br 500	Br 500	Br 500
BV2	Br 1000	Br 1000	Br 1000
BV3	Br 5000	Br 5000	Br 5000
BV4	Br 10000	Br 10000	Br 10000
BV5	Br 20000	Br 20000	Br 20000
BV6	Br 5(2009)	Br 5(2009)	Br 5(2009)
BV7	Br 10(2009)	Br 10(2009)	Br 10(2009)
BV8	Br 20(2009)	Br 20(2009)	