

L77F/PL77-KHR9

L77F/PL77-P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill KHR 100, 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 9bills.

(With stacker):

KHR 100, 500, 1000, 2000, 5000, 10000, 20000, 50000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	OFF	OFF							
2 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	OFF	ON							
3 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	ON	OFF							
4 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	OFF	ON	ON							
5 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	ON	OFF	OFF							
10 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	ON	OFF	ON							
20 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	ON	ON	OFF							
100 Pulses / KHR 100 (Note.3) KHR 500 (Note.4)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept KHR 100						ON				
Reject KHR 100						OFF				
★ Accept KHR 500 & 1000							ON			
Reject KHR 500 & 1000							OFF			
★ Accept KHR 2000 & 5000								ON		
Reject KHR 2000 & 5000								OFF		
★ Accept KHR 10000 & 20000									ON	
Reject KHR 10000 & 20000									OFF	
★ Accept KHR 50000 & 100000										ON
Reject KHR 50000 & 100000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Dip 6 turn ON (MDB Protocol : Reject KHR 50000 & KHR 100000).

(4) Dip 6 turn OFF (MDB Protocol : Accept KHR 50000 & KHR 100000).

L77F/PL77-KHR9 P2/P5 (Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Dip 6 ON				
Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	KHR 100	KHR 100	KHR 100	KHR 100
BV2	KHR 500	KHR 500	KHR 500	KHR 500
BV3	KHR 1000	KHR 1000	KHR 1000	KHR 1000
BV4	KHR 2000	KHR 2000	KHR 2000	KHR 2000
BV5	KHR 5000	KHR 5000	KHR 5000	KHR 5000
BV6	KHR 10000	KHR 10000	KHR 10000	KHR 10000
BV7	KHR 20000	KHR 20000	KHR 20000	KHR 20000
BV8	KHR 50000	KHR 50000		KHR 50000
BV9	KHR 100000	KHR 100000		KHR 100000

Currency Assign Data

Dip 6 OFF				
Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1		KHR 500	KHR 500	
BV2	KHR 500	KHR 1000	KHR 1000	KHR 500
BV3	KHR 1000	KHR 2000	KHR 2000	KHR 1000
BV4	KHR 2000	KHR 5000	KHR 5000	KHR 2000
BV5	KHR 5000	KHR 10000	KHR 10000	KHR 5000
BV6	KHR 10000	KHR 20000	KHR 20000	KHR 10000
BV7	KHR 20000	KHR 50000	KHR 50000	KHR 20000
BV8	KHR 50000	KHR 100000	KHR 100000	KHR 50000
BV9	KHR 100000			KHR 100000