

## L77F/PL77-RUB7

### L77F/PL77 Option Switch Settings : 1(Pulse/ICT104U/MDB/ccTalk)

Supported bill RUB 5, 10, 50, 100, 200, 500, 1000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RUB 5 or 10(Not4)	OFF	OFF	OFF							
	2 Pulses / RUB 5 or 10(Not4)	OFF	OFF	ON							
	3 Pulses / RUB 5 or 10(Not4)	OFF	ON	OFF							
	4 Pulses / RUB 5 or 10(Not4)	OFF	ON	ON							
	5 Pulses / RUB 5 or 10(Not4)	ON	OFF	OFF							
	10 Pulses / RUB 5 or 10(Not4)	ON	OFF	ON							
	20 Pulses / RUB 5 or 10(Not4)	ON	ON	OFF							
	100 Pulses / RUB 5 or 10(Not4)	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept RUB 5						ON				
	Reject RUB 5						OFF				
★	Accept RUB 10							ON			
	Reject RUB 10							OFF			
★	Accept RUB 50 & 100								ON		
	Reject RUB 50 & 100								OFF		
★	Accept RUB 200									ON	
	Reject RUB 200									OFF	
★	Accept RUB 500 & 1000										ON
	Reject RUB 500 & 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

(4) Pulse Mode: Accept RUB 5 ==> 1 Pulse / RUB 5  
Reject RUB 5 ==> 1 Pulse / RUB 10

## L77F/PL77-RUB7(Pulse/ICT104U/MDB/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	MDB Mode		ON	ON	OFF
★	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
★	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP)= 0	OFF			
★	MDB Mode		ON	ON	OFF
	Pulse Mode		ON	OFF	OFF
	ICT104U Mode		ON	OFF	ON

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch (Please see Nota.3 for Detail)		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ccTalk	ICT104U	Pulse	MDB
BV1	RUB 10	RUB 10	RUB 10	RUB 10
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	Reserved	Reserved	Reserved	Reserved
BV7	RUB 200	RUB 200	RUB 200	RUB 200
BV8	Reserved	Reserved	Reserved	Reserved
BV9	RUB 5	RUB 5	RUB 5	RUB 5