

L83-AMD2

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill AMD 1000, 2000 2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / AMD 1000	OFF	OFF	OFF							
	2 Pulse / AMD 1000	OFF	OFF	ON							
	3 Pulse / AMD 1000	OFF	ON	OFF							
	4 Pulse / AMD 1000	OFF	ON	ON							
	5 Pulse / AMD 1000	ON	OFF	OFF							
	10 Pulse / AMD 1000	ON	OFF	ON							
	20 Pulse / AMD 1000	ON	ON	OFF							
	100 Pulse / AMD 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept AMD 1000				ON						
	Reject AMD 1000				OFF						
★	Accept AMD 2000				ON						
	Reject AMD 2000				OFF						
★	Reserved				ON						
	Reserved				OFF						
★	Reserved				ON						
	Reserved				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note : Dip switches 1 to 5 are only used for pulse protocol.

L83 - AMD2(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	AMD 1000	AMD 1000	AMD 1000	AMD 1000
BV2	AMD 2000	AMD 2000	AMD 2000	AMD 2000

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting