

L83-EUR7

L83 Option Switch Settings : 1(Pulse/MDB/ccNet)

Supported bill € 5, 10, 20, 50, 100, 200, 500 7bills.

L83 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulse / € 5	OFF	OFF	ON							
3 Pulse / € 5	OFF	ON	OFF							
4 Pulse / € 5	OFF	ON	ON							
5 Pulse / € 5	ON	OFF	OFF							
10 Pulse / € 5	ON	OFF	ON							
20 Pulse / € 5	ON	ON	OFF							
100 Pulse / € 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>										
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept € 5 & 10				ON						
Reject € 5 & 10				OFF						
★ Accept € 20 & 50				ON						
Reject € 20 & 50				OFF						
★ Accept € 100				ON						
Reject € 100				OFF						
★ Accept € 200 & 500				ON						
Reject € 200 & 500				OFF						
★ Accept Normal				ON						
Reject € 5(2002) & 10(2002)				OFF						

◆ **Manufacture Default setting.**

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

L83-EUR7(Pulse/MDB/ccNet)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
MDB Interface		ON	ON	
ccNet Interface		OFF	OFF	
Reserved		OFF	ON	
Reserved				
★ Reserved				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Interface		ON	OFF	
MDB Interface		ON	ON	
★ ccNet Interface		OFF	OFF	
Reserved		OFF	ON	
★ Reserved				
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ccNet
BV1	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50
BV5	€ 100	€ 100	€ 100
BV6	€ 200	€ 200	€ 200
BV7	€ 500	€ 500	€ 500

Interface Settings: 2(MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Interface		ON	OFF	
★ MDB Interface		ON	ON	
ccNet Interface		OFF	OFF	
Reserved		OFF	ON	
★ Reserved				
				OFF

★ Manufacture setting