



GBP3

L83 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill £ 5, 10, 20 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / £ 5	OFF	OFF	OFF							
	2 Pulse / £ 5	OFF	OFF	ON							
	3 Pulse / £ 5	OFF	ON	OFF							
	4 Pulse / £ 5	OFF	ON	ON							
	5 Pulse / £ 5	ON	OFF	OFF							
	10 Pulse / £ 5	ON	OFF	ON							
	20 Pulse / £ 5	ON	ON	OFF							
	100 Pulse / £ 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept £ 5						ON				
	Reject £ 5						OFF				
★	Accept £ 10							ON			
	Reject £ 10							OFF			
★	Accept £ 20								ON		
	Reject £ 20								OFF		
★	Reserved									ON	
	Reserved									OFF	
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	£5	£5
BV2	£10	£10
BV3	£20	£20

L83-GBP3(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT Interface		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Interface		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting