

# L83-GHS8

## L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill GHS 1, 2, 5, 10, 20, 50, 100, 200 8bills.

|   | FUNCTION                                  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / GHS 1                           | OFF | OFF | OFF |     |     |     |     |     |     |      |
|   | 2 Pulses / GHS 1                          | OFF | OFF | ON  |     |     |     |     |     |     |      |
|   | 3 Pulses / GHS 1                          | OFF | ON  | OFF |     |     |     |     |     |     |      |
|   | 4 Pulses / GHS 1                          | OFF | ON  | ON  |     |     |     |     |     |     |      |
|   | 5 Pulses / GHS 1                          | ON  | OFF | OFF |     |     |     |     |     |     |      |
|   | 10 Pulses / GHS 1                         | ON  | OFF | ON  |     |     |     |     |     |     |      |
|   | 20 Pulses / GHS 1                         | ON  | ON  | OFF |     |     |     |     |     |     |      |
|   | 100 Pulses / GHS 1                        | ON  | ON  | ON  |     |     |     |     |     |     |      |
|   | Fast output Pulse<br>Lo= 50ms<br>Hi=100ms |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
|   | Inhibit level Active Low                  |     |     |     | ON  |     |     |     |     |     |      |
| ★ | Inhibit level Active High                 |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept GHS 1 & 2                          |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject GHS 1 & 2                          |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept GHS 5 & 10                         |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject GHS 5 & 10                         |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept GHS 20 & 50                        |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject GHS 20 & 50                        |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept GHS 100                            |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject GHS 100                            |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept GHS 200                            |     |     |     | ON  |     |     |     |     |     |      |
|   | Reject GHS 200                            |     |     |     | OFF |     |     |     |     |     |      |

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L83-GHS8(Pulse/ICT104U/MDB/ICT104V)

### DIP SWITCHES SETTING : 2(Pulse)

|   | FUNCTION                 | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal HIGH | ON  |     |     |     |
|   | Credit-Pulse Normal LOW  | OFF |     |     |     |
| ★ | Pulse Mode               |     | ON  | OFF |     |
|   | ICT104U Mode             |     | OFF | ON  |     |
|   | MDB Mode                 |     | ON  | ON  |     |
|   | ICT104V Mode             |     | OFF | OFF |     |
|   | Reserved                 |     |     |     | ON  |
| ★ |                          |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
| ★ | ICT104U Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
|   | ICT104V Mode |     | OFF | OFF |     |
|   | Reserved     |     |     |     | ON  |
| ★ |              |     |     |     | OFF |

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

|   | FUNCTION                                                      | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
|   | Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0   | OFF |     |     |     |
|   | Pulse Mode                                                    |     | ON  | OFF |     |
|   | ICT104U Mode                                                  |     | OFF | ON  |     |
| ★ | MDB Mode                                                      |     | ON  | ON  |     |
|   | ICT104V Mode                                                  |     | OFF | OFF |     |
|   | Reserved                                                      |     |     |     | ON  |
| ★ |                                                               |     |     |     | OFF |

★ Manufacture setting

## Currency Assign Data

| Interface<br>Bill value | Pulse   | MDB     | ICT104U | ICT104V |
|-------------------------|---------|---------|---------|---------|
| BV1                     | GHS 1   | GHS 1   | GHS 1   | GHS 1   |
| BV2                     | GHS 2   | GHS 2   | GHS 2   | GHS 2   |
| BV3                     | GHS 5   | GHS 5   | GHS 5   | GHS 5   |
| BV4                     | GHS 10  | GHS 10  | GHS 10  | GHS 10  |
| BV5                     | GHS 20  | GHS 20  | GHS 20  | GHS 20  |
| BV6                     | GHS 50  | GHS 50  | GHS 50  | GHS 50  |
| BV7                     | GHS 100 | GHS 100 | GHS 100 | GHS 100 |
| BV8                     | GHS 200 | GHS 200 | GHS 200 | GHS 200 |

### DIP SWITCHES SETTING : 2(ICT104V)

|   | FUNCTION     | SW1 | SW2 | SW3 | SW4 |
|---|--------------|-----|-----|-----|-----|
| ★ | Reserved     | ON  |     |     |     |
|   |              | OFF |     |     |     |
|   | Pulse Mode   |     | ON  | OFF |     |
|   | ICT104U Mode |     | OFF | ON  |     |
|   | MDB Mode     |     | ON  | ON  |     |
| ★ | ICT104V Mode |     | OFF | OFF |     |
|   | Reserved     |     |     |     | ON  |
| ★ |              |     |     |     | OFF |

★ Manufacture setting