

L83-IQD5

L83/P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill IQD 250, 500, 1000, 5000, 10000 5bills.
with stacker bill IQD 250, 500, 1000, 5000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / IQD 250	OFF	OFF	OFF							
	2 Pulse / IQD 250	OFF	OFF	ON							
	3 Pulse / IQD 250	OFF	ON	OFF							
	4 Pulse / IQD 250	OFF	ON	ON							
	5 Pulse / IQD 250	ON	OFF	OFF							
	10 Pulse / IQD 250	ON	OFF	ON							
	20 Pulse / IQD 250	ON	ON	OFF							
	100 Pulse / IQD 250	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept IQD 250				ON						
	Reject IQD 250				OFF						
★	Accept IQD 500				ON						
	Reject IQD 500				OFF						
★	Accept IQD 1000				ON						
	Reject IQD 1000				OFF						
★	Accept IQD 5000				ON						
	Reject IQD 5000				OFF						
★	Accept IQD 10000				ON						
	Reject IQD 10000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

L83-IQD5(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB
BV1	IQD 250	IQD 250	IQD 250
BV2	IQD 500	IQD 500	IQD 500
BV3	IQD 1000	IQD 1000	IQD 1000
BV4	IQD 5000	IQD 5000	IQD 5000
BV5	IQD 10000	IQD 10000	IQD 10000

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 1000 Decimal Point Position (DPP) = 3	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting