

L83-MAD4

L83 DIP SWITCHES SETTING : 1(Pulse/ICT/MDB)

Supported bill MAD 20, 50, 100, 200 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MAD 10	OFF	OFF	OFF							
	2 Pulse / MAD 10	OFF	OFF	ON							
	3 Pulse / MAD 10	OFF	ON	OFF							
	4 Pulse / MAD 10	OFF	ON	ON							
	5 Pulse / MAD 10	ON	OFF	OFF							
	10 Pulse / MAD 10	ON	OFF	ON							
	20 Pulse / MAD 10	ON	ON	OFF							
	100 Pulse / MAD 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms										
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MAD 20				ON						
	Reject MAD 20				OFF						
★	Accept MAD 50				ON						
	Reject MAD 50				OFF						
★	Accept MAD 100				ON						
	Reject MAD 100				OFF						
★	Accept MAD 200				ON						
	Reject MAD 200				OFF						
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-MAD4(Pulse/ICT/MDB)

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	Pulse	ICT104	MDB_EU
BV1	MAD 20	MAD 20	MAD 20
BV2	MAD 50	MAD 50	MAD 50
BV3	MAD 100	MAD 100	MAD 100
BV4	MAD 200	MAD 200	MAD 200

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104 Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104 Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting