

L83-UAH9

L83-P3/P6 DIP SWITCHES SETTING : 1(ccTalk/RS232 A1/RS232 A0)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500
9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserve	ON									
		OFF									
★	Reserve		ON								
			OFF								
★	Reserve			ON							
				OFF							
★	Reserve				ON						
					OFF						
★	Reserve					ON					
						OFF					
★	Accept HRYVEN 1 & 2						ON				
	Reject HRYVEN 1 & 2						OFF				
★	Accept HRYVEN 5 & 10 & 20 & 50							ON			
	Reject HRYVEN 5 & 10 & 20 & 50							OFF			
★	Accept HRYVEN 100 & 200								ON		
	Reject HRYVEN 100 & 200								OFF		
★	Accept HRYVEN 500									ON	
	Reject HRYVEN 500									OFF	
	Simulation BillBox Has Been Removed										ON
★	Default										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L83-UAH9(ccTalk/RS232 A1/RS232 A0)

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	ccTalk Parameters Restore Switch Please see "Note" for detail			ON	
	ccTalk Interface			OFF	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

RS232 A0 INFORMATION

BillType Data		
Code	Denomination	
1	HRYPEN	1
2	HRYPEN	2
3	HRYPEN	5
4	HRYPEN	10
5	HRYPEN	20
6	HRYPEN	50
7	HRYPEN	100
8	HRYPEN	200
9	HRYPEN	500

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A1)

	FUNCTION	SW1	SW2	SW3	SW4
★	ccTalk	OFF	OFF		
	RS232 A0	ON	OFF		
	RS232 A1	OFF	ON		
	Reserved	ON	ON		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	RS232 A0	RS232 A1	ccTalk
BV1	HRYPEN 1	HRYPEN 1	HRYPEN 1
BV2	HRYPEN 2	HRYPEN 2	HRYPEN 2
BV3	HRYPEN 5	HRYPEN 5	HRYPEN 5
BV4	HRYPEN 10	HRYPEN 10	HRYPEN 10
BV5	HRYPEN 20	HRYPEN 20	HRYPEN 20
BV6	HRYPEN 50	HRYPEN 50	HRYPEN 50
BV7	HRYPEN 100	HRYPEN 100	HRYPEN 100
BV8	HRYPEN 200	HRYPEN 200	HRYPEN 200
BV9	HRYPEN 500	HRYPEN 500	HRYPEN 500