



UGX6

L83 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill UGX 1000, 2000, 5000, 10000, 20000,
50000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / UGX 1000	OFF	OFF	OFF								
	2 Pulse / UGX 1000	OFF	OFF	ON								
	3 Pulse / UGX 1000	OFF	ON	OFF								
	4 Pulse / UGX 1000	OFF	ON	ON								
	5 Pulse / UGX 1000	ON	OFF	OFF								
	10 Pulse / UGX 1000	ON	OFF	ON								
	20 Pulse / UGX 1000	ON	ON	OFF								
	100 Pulse / UGX 1000	ON	ON	ON								
	Fast output Pulse	Lo= 50ms Hi=100ms			ON							
★	Slow output Pulse	Lo= 50ms Hi=300ms			OFF							
	Inhibit level Active Low					ON						
★	Inhibit level Active High					OFF						
★	Accept UGX 1000 & 2000						ON					
	Reject UGX 1000 & 2000						OFF					
★	Accept UGX 5000								ON			
	Reject UGX 5000								OFF			
★	Accept UGX 10000									ON		
	Reject UGX 10000									OFF		
★	Accept UGX 20000										ON	
	Reject UGX 20000										OFF	
★	Accept UGX 50000											ON
	Reject UGX 50000											OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Protocol Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

