

L83-XAF5

L83 Option Switch Settings : 1(Pulse/V2.2/RS232 A0)

Supported bill Fr 500, 1000, 2000, 5000, 10000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Fr 500	OFF	OFF	OFF							
	2 Pulses / Fr 500	OFF	OFF	ON							
	5 Pulses / Fr 500	OFF	ON	OFF							
	10 Pulses / Fr 500	OFF	ON	ON							
	20 Pulses / Fr 500	ON	OFF	OFF							
	50 Pulses / Fr 500	ON	OFF	ON							
	100 Pulses / Fr 500	ON	ON	OFF							
	200 Pulses / Fr 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Fr 500						ON				
	Reject Fr 500						OFF				
★	Accept Fr 1000							ON			
	Reject Fr 1000							OFF			
★	Accept Fr 2000								ON		
	Reject Fr 2000								OFF		
★	Accept Fr 5000									ON	
	Reject Fr 5000									OFF	
★	Accept Fr 10000										ON
	Reject Fr 10000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-XAF5(Pulse/V2.2/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	RS232 A0 Mode		ON	ON	
★	Pulse Mode		ON	OFF	
	Reserved		OFF	OFF	
	V2.2 Mode		OFF	ON	
★	Reserved				ON OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
★	RS232 A0 Mode		ON	ON	
	Pulse Mode		ON	OFF	
	Reserved		OFF	OFF	
	V2.2 Mode		OFF	ON	
★	Reserved				ON OFF

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	Fr 500
4	Fr 1000
5	Fr 2000
6	Fr 5000
7	Fr 10000
8	Reserved

★ Manufacture setting

DIP SWITCHES SETTING : 2(V2.2)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
	RS232 A0 Mode		ON	ON	
	Pulse Mode		ON	OFF	
	Reserved		OFF	OFF	
★	V2.2 Mode		OFF	ON	
★	Reserved				ON OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	Fr 500	Fr 500	Fr 500
BV2	Fr 1000	Fr 1000	Fr 1000
BV3	Fr 2000	Fr 2000	Fr 2000
BV4	Fr 5000	Fr 5000	Fr 5000
BV5	Fr 10000	Fr 10000	Fr 10000