

## NE77-EUR4

### NE77 DIP SWITCHES SETTING : (ICT104U/Pulse/ccTalk)

Supported bill EUR 5, 10, 20, 50

4bills.

#### DIP SWITCHES SETTING : (ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserved	ON									
★	Reserved	OFF									
★	ccTalk Potocol		ON								
★	ICT104U Potocol		OFF								
★	Reserved			ON							
★	Reserved			OFF							
★	Enable Output Sensor Detect				ON						
★	Disable Output Sensor Detect				OFF						
★	Reserved				ON						
★	Reserved				OFF						
★	Optical anti-fishing malfunction, BA will be still in working order					ON					
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction					OFF					
★	Euro 5 & 10							OFF	OFF		
★	Euro 10 & 20 & 50							OFF	ON		
★	Euro 5 & 10 & 20							ON	OFF		
★	Euro 5 & 10 & 20 & 50							ON	ON		
★	Operation Mode									ON	
★	Diagnostic Mode									OFF	
★	Pulse Protocol										ON
★	Other Protocol										OFF

★ Manufacture setting

Note1 : Please restart the bill acceptor after any changes on dip switch(s) has been made.

Note2 : Turn this dip to with restart the bill acceptor will restore  
ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

## NE77-EUR4 (ICT104U/Pulse/ccTalk)

### DIP SWITCHES SETTING : (Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	5 Pulse / € 5	ON									
★	1 Pulse / € 5	OFF									
★	Lo=150ms / Hi=180ms		OFF	OFF							
★	Lo=100ms / Hi=100ms		OFF	ON							
★	Lo= 50ms / Hi=100ms		ON	OFF							
★	Lo= 50ms / Hi= 50ms		ON	ON							
★	Enable Output Sensor Detect				ON						
★	Disable Output Sensor Detect				OFF						
★	Inhibit level Active High					ON					
★	Inhibit level Active Low					OFF					
★	Optical anti-fishing malfunction, BA will be still in working order						ON				
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction						OFF				
★	Euro 5 & 10							OFF	OFF		
★	Euro 10 & 20 & 50							OFF	ON		
★	Euro 5 & 10 & 20							ON	OFF		
★	Euro 5 & 10 & 20 & 50							ON	ON		
★	Operation Mode									ON	
★	Diagnostic Mode									OFF	
★	Pulse Protocol										ON
★	Other Protocol										OFF

### DIP SWITCHES SETTING : (ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserved	ON									
★	Reserved	OFF									
★	ccTalk Protocol		ON								
★	ICT104U Protocol		OFF								
★	Encyption MODE			ON							
★	Decrypt MODE			OFF							
★	Enable Output Sensor Detect				ON						
★	Disable Output Sensor Detect				OFF						
★	ccTalk parameters restore (Please see Note.2 for detail)					ON					
★	ccTalk parameters not restore					OFF					
★	Optical anti-fishing malfunction, BA will be still in working order						ON				
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction						OFF				
★	Euro 5 & 10							OFF	OFF		
★	Euro 10 & 20 & 50							OFF	ON		
★	Euro 5 & 10 & 20							ON	OFF		
★	Euro 5 & 10 & 20 & 50							ON	ON		
★	Operation Mode									ON	
★	Diagnostic Mode									OFF	
★	Pulse Proctol										ON
★	Other Proctol										OFF