

S7A II-AUD5 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill AUD 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AUD 5 & 10	ON											
★ Accept AUD 5 & 10	OFF											
★ Reject AUD 20		ON										
★ Accept AUD 20		OFF										
★ Reject AUD 50			ON									
★ Accept AUD 50			OFF									
★ Reject AUD 100				ON								
★ Accept AUD 100				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Other Interface	Test Mode (No Communication)							ON				
	Operation Mode							OFF				
★ Pulse Mode	Inhibit Active HIGH (Test)							ON				
	Inhibit Active LOW							OFF				
★ ENABLE IrDA Download								ON				
★ Reserved								OFF				
★ ENABLE INHIBIT-Sleep Only									ON			
★ 5 second Timeout Only									OFF			
NORMAL										OFF	OFF	
MODE1										OFF	ON	
MODE2										ON	OFF	
★ MODE1+2										ON	ON	

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note:

NORMAL: No sleep function

MODE 1: Bill-acceptor wakes up VMC with banknote only (special cable required)

MODE 2: VMC wakes up bill-acceptor

MODE 1+2: Bill-acceptor wakes up with banknote or by VMC

Note 1. Normal pulse :When DIP-SW1 is ON ,AUD 5=1 pulse,or 2 pulses,or 4 pulses,or 20 pulses.

Special pulse:When DIP-SW1 is OFF ,AUD 5=1 pulse,or 3 pulses,or 5 pulses,or 6 pulses.

Appendix

S7A II-AUD5(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Normal pulse (Note 1)	ON			
Special pulse (Note 1)	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse & 1 pulse / AUD 5	(Note.1)		OFF	OFF
2 pulses & 3 pulses / AUD 5	(Note.1)		OFF	ON
4 pulses & 5 pulses / AUD 5	(Note.1)		ON	OFF
20 pulses & 6 pulses / AUD 5	(Note.1)		ON	ON

★ Manufacture setting

Note:1. Normal pulse :When DIP-SW1 is OFF,
AUD 5=1 Pulse, or 2 Pulses, or 4 Pulses,
or 20 Pulses.
Special Pulse: When DIP-SW1 is ON ,
AUD 5=1 Pulse, or 3 Pulses,
or 5 Pulses, or 6 pulses.

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB			OFF	OFF
ICT104U			OFF	ON
Reserved			ON	ON
Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB			OFF	OFF
★ ICT104U			OFF	ON
Reserved			ON	ON
Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ Other Mode		OFF		
MDB			OFF	OFF
ICT104U			OFF	ON
Reserved			ON	ON
★ Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	AUD 5	AUD 5	AUD 5	AUD 5
BV2	AUD 10	AUD 10	AUD 10	AUD 10
BV3	AUD 20	AUD 20	AUD 20	AUD 20
BV4	AUD 50	AUD 50	AUD 50	AUD 50
BV5	AUD 100	AUD 100	AUD 100	