

## S7A II-GEL4 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill Lari 5, 10, 20, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4		
★	Reject Lari 5	ON													
	Accept Lari 5	OFF													
★	Reject Lari 10		ON												
	Accept Lari 10		OFF												
★	Reject Lari 20			ON											
	Accept Lari 20			OFF											
★	Reject Lari 50				ON										
	Accept Lari 50				OFF										
★	Reserved					ON									
	Reserved					OFF									
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON								
	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF								
★	Stack Banknote when Power-up							ON							
	Reject Banknote when Power-up							OFF							
★	Other Interface	Test Mode (No Communication)							ON						
		Operation Mode							OFF						
★	Pulse Mode	Inhibit Active HIGH (Test)							ON						
		Inhibit Active LOW							OFF						
★	ENABLE IrDA Download									ON					
	Reserved									OFF					
★	Reserved										ON				
	Reserved										OFF				
★	Reserved											ON			
	Reserved											OFF			
★	Reserved												ON		
	Reserved												OFF		
★	Reserved													ON	
	Reserved													OFF	

★ Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

## S7A II-GEL4(Pulse/MDB/ICT104U/Parallel A3)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
★	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	1 pulse / Lari 5			OFF	OFF
	2 pulses / Lari 5			OFF	ON
	5 pulses / Lari 5			ON	OFF
	20 pulses / Lari 5			ON	ON

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	Lari 5	Lari 5	Lari 5	Lari 5
BV2	Lari 10	Lari 10	Lari 10	Lari 10
BV3	Lari 20	Lari 20	Lari 20	Lari 20
BV4	Lari 50	Lari 50	Lari 50	Lari 50