

S7A II-PHP6 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject P 20	ON											
★	Accept P 20	OFF											
★	Reject P 50		ON										
★	Accept P 50		OFF										
★	Reject P 100 & 200			ON									
★	Accept P 100 & 200			OFF									
★	Reject P 500 & 1000				ON								
★	Accept P 500 & 1000				OFF								
★	Enable, if fishing, BA doesn't work any more					ON							
★	Disable, BA works normally					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
★	Reject Banknote when Power-up							OFF					
★	Other Interface	Test Mode (No Communication)							ON				
		Operation Mode							OFF				
★	Pulse Mode	Inhibit Active HIGH (Test)							ON				
		Inhibit Active LOW							OFF				
★	ENABLE IrDA Download								ON				
★	Reserved								OFF				
★	ENABLE INHIBIT-Sleep Only									ON			
★	5 second Timeout Only									OFF			
	NORMAL										OFF	OFF	
	MODE1										OFF	ON	
	MODE2										ON	OFF	
★	MODE1+2										ON	ON	

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note:

NORMAL: No sleep function

MODE 1: Bill-acceptor wakes up VMC with banknote only (special cable required)

MODE 2: VMC wakes up bill-acceptor

MODE 1+2: Bill-acceptor wakes up with banknote or by VMC

S7A II-PHP6(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / P 10			OFF	OFF
	5 pulses / P 10			OFF	ON
	10 pulses / P 10			ON	OFF
	20 pulses / P 10			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	Parallel A3
BV1	P 20	P 20	P 20	P 20
BV2	P 50	P 50	P 50	P 50
BV3	P 100	P 100	P 100	P 100
BV4	P 500	P 200	P 200	P 200
BV5	P 1000	P 500	P 500	
BV6	P 200	P 1000	P 1000	