

S7ER-MXN5 Option Switch Settings: (Pulse)

Supported bill M\$ 20, 50, 100, 200, 500

5bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject M\$ 20	ON															
Accept M\$ 20	OFF															
Reject M\$ 50		ON														
Accept M\$ 50		OFF														
Reject M\$ 100			ON													
Accept M\$ 100			OFF													
Reject M\$ 200				ON												
Accept M\$ 200				OFF												
Reject M\$ 500					ON											
Accept M\$ 500					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec					ON											
Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF											
Stack Banknote when Power-up						ON										
Reject Banknote when Power-up						OFF										
Inhibit Active HIGH							ON									
Inhibit Active LOW							OFF									
Pulse Speed	100ms LO / 100ms HI						ON									
	50ms LO / 50ms HI						OFF									
Reserve								ON								
								OFF								
Normal									OFF	OFF						
Mode 1										OFF	ON					
Mode 2										ON	OFF					
Mode 1 + 2										ON	ON					
Credit-Pulse Normal HIGH									ON							
Credit-Pulse Normal LOW									OFF							
Pulse Mode										ON						
ICT Mode										OFF						
1 pulse / M\$ 10											OFF	OFF				
5 pulses / M\$ 10												OFF	ON			
10 pulses / M\$ 10												ON	OFF			
25 pulses / M\$ 10												ON	ON			

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

Appendix

S7ER-MXN5 (ICT106S)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject M\$ 20	ON															
Accept M\$ 20	OFF															
Reject M\$ 50		ON														
Accept M\$ 50		OFF														
Reject M\$ 100			ON													
Accept M\$ 100			OFF													
Reject M\$ 200				ON												
Accept M\$ 200				OFF												
Reject M\$ 500					ON											
Accept M\$ 500					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec					ON											
Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF											
Stack Banknote when Power-up						ON										
Reject Banknote when Power-up						OFF										
Test Mode							ON									
Reserved							OFF									
Pulse Speed	100ms LO / 100ms HI						ON									
	50ms LO / 50ms HI						OFF									
Reserved								ON								
								OFF								
Normal									OFF	OFF						
Mode 1										OFF	ON					
Mode 2										ON	OFF					
Mode 1 + 2										ON	ON					
Reserved									ON							
Reserved									OFF							
Pulse Mode										ON						
ICT Mode										OFF						
Reserved											ON					
Reserved											OFF					
Reserved												ON				
Reserved													OFF			

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	M\$ 20	M\$ 20
BV2	M\$ 50	M\$ 50
BV3	M\$ 100	M\$ 100
BV4	M\$ 200	M\$ 200
BV5	M\$ 500	M\$ 500