

S7ER-MYR6 Option Switch Settings: (Pulse)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

S7ER dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 | SW1 | SW2 | SW3 | SW4 |
|--|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject M\$ 1 | ON | | | | | | | | | | | | | | | |
| ★ Accept M\$ 1 | OFF | | | | | | | | | | | | | | | |
| ★ Reject M\$ 5 | | ON | | | | | | | | | | | | | | |
| ★ Accept M\$ 5 | | OFF | | | | | | | | | | | | | | |
| ★ Reject M\$ 10 & 20 | | | ON | | | | | | | | | | | | | |
| ★ Accept M\$ 10 & 20 | | | OFF | | | | | | | | | | | | | |
| ★ Reject M\$ 50 | | | | ON | | | | | | | | | | | | |
| ★ Accept M\$ 50 | | | | OFF | | | | | | | | | | | | |
| ★ Reject M\$ 100 | | | | | ON | | | | | | | | | | | |
| ★ Accept M\$ 100 | | | | | OFF | | | | | | | | | | | |
| ★ Disable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | ON | | | | | | | | | | |
| ★ Enable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | OFF | | | | | | | | | | |
| ★ Stack Banknote when Power-up | | | | | | | ON | | | | | | | | | |
| ★ Reject Banknote when Power-up | | | | | | | OFF | | | | | | | | | |
| ★ Inhibit Active HIGH | | | | | | | | ON | | | | | | | | |
| ★ Inhibit Active LOW | | | | | | | | OFF | | | | | | | | |
| ★ Pulse Speed | 100ms on / 100ms off | | | | | | ON | | | | | | | | | |
| | 50ms on / 50ms off | | | | | | OFF | | | | | | | | | |
| ★ ENABLE INHIBIT-Sleep only | | | | | | | | | ON | | | | | | | |
| ★ 5 second Timeout only | | | | | | | | | OFF | | | | | | | |
| ★ Normal | | | | | | | | | | | OFF | OFF | | | | |
| ★ Mode 1 | | | | | | | | | | | OFF | ON | | | | |
| ★ Mode 2 | | | | | | | | | | | ON | OFF | | | | |
| ★ Mode 1 + 2 | | | | | | | | | | | ON | ON | | | | |
| ★ Credit-Pulse Normal HIGH Enable Optical anti-stringing design | | | | | | | | | | | ON | | | | | |
| ★ Credit-Pulse Normal LOW Disable Optical anti-stringing design | | | | | | | | | | | OFF | | | | | |
| ★ Pulse Mode | | | | | | | | | | | | | ON | | | |
| ★ ICT Mode | | | | | | | | | | | | | OFF | | | |
| ★ 1 pulse / M\$ 1 | | | | | | | | | | | | | OFF | OFF | | |
| ★ 5 pulses / M\$ 1 | | | | | | | | | | | | | OFF | ON | | |
| ★ 10 pulses / M\$ 1 | | | | | | | | | | | | | ON | OFF | | |
| ★ 25 pulses / M\$ 1 | | | | | | | | | | | | | ON | ON | | |

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.
3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).
4. Mode 2 : VMC wakes up bill-acceptor.
5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

S7ER-MYR6 (ICT)

S7ER dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 | SW1 | SW2 | SW3 | SW4 |
|--|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject M\$ 1 | ON | | | | | | | | | | | | | | | |
| ★ Accept M\$ 1 | OFF | | | | | | | | | | | | | | | |
| ★ Reject M\$ 5 | | ON | | | | | | | | | | | | | | |
| ★ Accept M\$ 5 | | OFF | | | | | | | | | | | | | | |
| ★ Reject M\$ 10 & 20 | | | ON | | | | | | | | | | | | | |
| ★ Accept M\$ 10 & 20 | | | OFF | | | | | | | | | | | | | |
| ★ Reject M\$ 50 | | | | ON | | | | | | | | | | | | |
| ★ Accept M\$ 50 | | | | OFF | | | | | | | | | | | | |
| ★ Reject M\$ 100 | | | | | ON | | | | | | | | | | | |
| ★ Accept M\$ 100 | | | | | OFF | | | | | | | | | | | |
| ★ Disable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | ON | | | | | | | | | | |
| ★ Enable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | OFF | | | | | | | | | | |
| ★ Stack Banknote when Power-up | | | | | | | ON | | | | | | | | | |
| ★ Reject Banknote when Power-up | | | | | | | OFF | | | | | | | | | |
| ★ Test Mode | | | | | | | | ON | | | | | | | | |
| ★ Reserved | | | | | | | | OFF | | | | | | | | |
| ★ Pulse Speed | 100ms on / 100ms off | | | | | | ON | | | | | | | | | |
| | 50ms on / 50ms off | | | | | | OFF | | | | | | | | | |
| ★ ENABLE INHIBIT-Sleep only | | | | | | | | | ON | | | | | | | |
| ★ 5 second Timeout only | | | | | | | | | OFF | | | | | | | |
| ★ Normal | | | | | | | | | | | OFF | OFF | | | | |
| ★ Mode 1 | | | | | | | | | | | OFF | ON | | | | |
| ★ Mode 2 | | | | | | | | | | | ON | OFF | | | | |
| ★ Mode 1 + 2 | | | | | | | | | | | ON | ON | | | | |
| ★ ENABLE Optical anti-stringing design | | | | | | | | | | | ON | | | | | |
| ★ DISABLE Optical anti-stringing design | | | | | | | | | | | OFF | | | | | |
| ★ Pulse Mode | | | | | | | | | | | | | ON | | | |
| ★ ICT Mode | | | | | | | | | | | | | OFF | | | |
| ★ Reserved | | | | | | | | | | | | | | | OFF | OFF |
| ★ Reserved | | | | | | | | | | | | | | | ON | OFF |
| ★ Reserved | | | | | | | | | | | | | | | ON | ON |

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.
3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).
4. Mode 2 : VMC wakes up bill-acceptor.
5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.
6. BV1=M\$ 1 · BV3=M\$ 5 · BV4=M\$ 10 · BV5=M\$ 50 · BV6=M\$ 100 · BV7=M\$ 20.