

S7ER-THB4 Option Switch Settings: (Pulse)

Supported bill THB 20, 50, 100, 500 4bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject THB 20	ON															
Accept THB 20	OFF															
Reject THB 50		ON														
Accept THB 50		OFF														
Reject THB 100			ON													
Accept THB 100			OFF													
Reject THB 500				ON												
Accept THB 500				OFF												
High Acceptance					ON											
High Security(*)					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
Stack Banknote when Power-up							ON									
Reject Banknote when Power-up							OFF									
Inhibit Active HIGH								ON								
Inhibit Active LOW								OFF								
Pulse Speed	100ms HI / 100ms LO							ON								
	50ms HI / 50ms LO							OFF								
Reserved									ON							
Reserved									OFF							
Normal										OFF	OFF					
Mode 1											OFF	ON				
Mode 2											ON	OFF				
Mode 1 + 2											ON	ON				
Credit-Pulse Normal HIGH												ON				
Credit-Pulse Normal LOW												OFF				
Pulse Mode													ON			
ICT106S Mode													OFF			
1 pulse / THB 10														OFF	OFF	
5 pulses / THB 10															OFF	ON
10 pulses / THB 10															ON	OFF
25 pulses / THB 10															ON	ON

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

* High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

S7ER-THB4 (ICT106S)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject THB 20	ON															
Accept THB 20	OFF															
Reject THB 50		ON														
Accept THB 50		OFF														
Reject THB 100			ON													
Accept THB 100			OFF													
Reject THB 500				ON												
Accept THB 500				OFF												
High Acceptance					ON											
High Security(*)					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
Stack Banknote when Power-up							ON									
Reject Banknote when Power-up							OFF									
Test Mode								ON								
Reserved								OFF								
Reserved									ON							
Reserved									OFF							
Reserved										ON						
Reserved										OFF						
Normal											OFF	OFF				
Mode 1												OFF	ON			
Mode 2												ON	OFF			
Mode 1 + 2												ON	ON			
Reserved													ON			
Reserved													OFF			
Pulse Mode														ON		
ICT106S Mode															OFF	
Reserved															ON	
Reserved															OFF	
Reserved																ON
Reserved																OFF

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

* High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500