

S7ER-TTD6 Option Switch Settings: (Pulse)

Supported bill TTD 1, 5, 10, 20, 50, 100 6bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject TTD 1 & 5	ON															
★ Accept TTD 1 & 5	OFF															
★ Reject TTD 10		ON														
★ Accept TTD 10		OFF														
★ Reject TTD 20			ON													
★ Accept TTD 20			OFF													
★ Reject TTD 50				ON												
★ Accept TTD 50				OFF												
★ Reject TTD 100					ON											
★ Accept TTD 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Inhibit Active HIGH								ON								
★ Inhibit Active LOW								OFF								
★ Pulse Speed	100ms LO / 100ms HI							ON								
	50ms LO / 50ms HI							OFF								
★ Reserved									ON							
									OFF							
★ Reserved										ON						
										OFF						
★ Reserved											ON					
											OFF					
★ Reserved												ON				
												OFF				
★ Credit-Pulse Normal HIGH													ON			
★ Credit-Pulse Normal LOW													OFF			
★ Pulse Mode														ON		
★ ICT002 Mode														OFF		
★ 1 pulse / TTD 1															OFF	OFF
★ 2 pulses / TTD 1															OFF	ON
★ 4 pulses / TTD 1															ON	OFF
★ 20 pulses / TTD 1															ON	ON

★ Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

S7ER-TTD6 (ICT002)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject TTD 1 & 5	ON															
★ Accept TTD 1 & 5	OFF															
★ Reject TTD 10		ON														
★ Accept TTD 10		OFF														
★ Reject TTD 20			ON													
★ Accept TTD 20			OFF													
★ Reject TTD 50				ON												
★ Accept TTD 50				OFF												
★ Reject TTD 100					ON											
★ Accept TTD 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Test Mode (No Communication)								ON								
★ Operation Mode								OFF								
★ Reserved									ON							
									OFF							
★ Reserved										ON						
										OFF						
★ Reserved											ON					
											OFF					
★ Reserved												ON				
												OFF				
★ Reserved													ON			
★ Reserved													OFF			
★ Pulse Mode														ON		
★ ICT002 Mode														OFF		
★ Reserved															ON	
★ Reserved															OFF	
★ Reserved																ON
★ Reserved																OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.No RFID function.

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	TTD 1	TTD 1
BV2	TTD 5	TTD 5
BV3	TTD 10	TTD 10
BV4	TTD 20	TTD 20
BV5	TTD 100	TTD 100
BV6	TTD 50	TTD 50