

S7ER-TWD4 Option Switch Settings: (Pulse)

Supported bill TWD 100, 200, 500, 1000 4bills.

S7ER dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 | SW1 | SW2 | SW3 | SW4 |
|--|---------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject TWD 100 | ON | | | | | | | | | | | | | | | |
| ★ Accept TWD 100 | OFF | | | | | | | | | | | | | | | |
| ★ Reject TWD 200 | | ON | | | | | | | | | | | | | | |
| ★ Accept TWD 200 | | OFF | | | | | | | | | | | | | | |
| ★ Reject TWD 500 | | | ON | | | | | | | | | | | | | |
| ★ Accept TWD 500 | | | OFF | | | | | | | | | | | | | |
| ★ Reject TWD 1000 | | | | ON | | | | | | | | | | | | |
| ★ Accept TWD 1000 | | | | OFF | | | | | | | | | | | | |
| ★ Reserve | | | | | ON | | | | | | | | | | | |
| ★ Reserve | | | | | OFF | | | | | | | | | | | |
| ★ Disable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | ON | | | | | | | | | | |
| ★ Enable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | OFF | | | | | | | | | | |
| ★ Stack Banknote when Power-up | | | | | | | ON | | | | | | | | | |
| ★ Reject Banknote when Power-up | | | | | | | OFF | | | | | | | | | |
| ★ Inhibit Active HIGH | | | | | | | | ON | | | | | | | | |
| ★ Inhibit Active LOW | | | | | | | | OFF | | | | | | | | |
| ★ Pulse Speed | 100ms HI / 100ms LO | | | | | | | ON | | | | | | | | |
| | 50ms HI / 50ms LO | | | | | | | OFF | | | | | | | | |
| ★ Reserve | | | | | | | | | ON | | | | | | | |
| | | | | | | | | | OFF | | | | | | | |
| ★ Reserve | | | | | | | | | | ON | | | | | | |
| | | | | | | | | | | OFF | | | | | | |
| ★ Reserve | | | | | | | | | | | ON | | | | | |
| | | | | | | | | | | | OFF | | | | | |
| ★ Credit-Pulse Normal HIGH | | | | | | | | | | | | | ON | | | |
| ★ Credit-Pulse Normal LOW | | | | | | | | | | | | | OFF | | | |
| ★ Pulse Mode | | | | | | | | | | | | | | ON | | |
| ★ ICT Mode | | | | | | | | | | | | | | OFF | | |
| ★ 1 pulse / TWD 100 | | | | | | | | | | | | | | | OFF | OFF |
| ★ 2 pulses / TWD 100 | | | | | | | | | | | | | | | OFF | ON |
| ★ 10 pulses / TWD 100 | | | | | | | | | | | | | | | ON | OFF |
| ★ 20 pulses / TWD 100 | | | | | | | | | | | | | | | ON | ON |

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

S7ER-TWD4 (ICT104U)

S7ER dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 | SW1 | SW2 | SW3 | SW4 | |
|--|---------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject TWD 100 | ON | | | | | | | | | | | | | | | | |
| ★ Accept TWD 100 | OFF | | | | | | | | | | | | | | | | |
| ★ Reject TWD 200 | | ON | | | | | | | | | | | | | | | |
| ★ Accept TWD 200 | | OFF | | | | | | | | | | | | | | | |
| ★ Reject TWD 500 | | | ON | | | | | | | | | | | | | | |
| ★ Accept TWD 500 | | | OFF | | | | | | | | | | | | | | |
| ★ Reject TWD 1000 | | | | ON | | | | | | | | | | | | | |
| ★ Accept TWD 1000 | | | | OFF | | | | | | | | | | | | | |
| ★ Reserve | | | | | ON | | | | | | | | | | | | |
| ★ Reserve | | | | | OFF | | | | | | | | | | | | |
| ★ Disable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | ON | | | | | | | | | | | |
| ★ Enable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | OFF | | | | | | | | | | | |
| ★ Stack Banknote when Power-up | | | | | | | ON | | | | | | | | | | |
| ★ Reject Banknote when Power-up | | | | | | | OFF | | | | | | | | | | |
| ★ Test Mode | | | | | | | | ON | | | | | | | | | |
| ★ Reserved | | | | | | | | OFF | | | | | | | | | |
| ★ Pulse Speed | 100ms HI / 100ms LO | | | | | | | ON | | | | | | | | | |
| | 50ms HI / 50ms LO | | | | | | | OFF | | | | | | | | | |
| ★ Reserved | | | | | | | | | ON | | | | | | | | |
| | | | | | | | | | OFF | | | | | | | | |
| ★ Reserved | | | | | | | | | | ON | | | | | | | |
| | | | | | | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | | | | | | ON | | | | | | |
| | | | | | | | | | | | OFF | | | | | | |
| ★ Pulse Mode | | | | | | | | | | | | | ON | | | | |
| ★ ICT Mode | | | | | | | | | | | | | | OFF | | | |
| ★ Reserved | | | | | | | | | | | | | | | ON | | |
| ★ Reserved | | | | | | | | | | | | | | | | OFF | |
| ★ Reserved | | | | | | | | | | | | | | | | | ON |
| ★ Reserved | | | | | | | | | | | | | | | | | OFF |

★ Manufacture setting

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Currency Assign Data

| Interface Bill value | ICT | Pulse |
|-------------------------|----------|----------|
| BV1 | TWD 100 | TWD 100 |
| BV2 | TWD 200 | TWD 200 |
| BV3 | TWD 500 | TWD 500 |
| BV4 | TWD 1000 | TWD 1000 |