

## V7P-BAM3

### V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill BAM 10, 20, 50 3bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject BAM 10	ON											
★ Accept BAM 10	OFF											
★ Reject BAM 20		ON										
★ Accept BAM 20		OFF										
★ Reject BAM 50			ON									
★ Accept BAM 50			OFF									
Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / BAM 10									OFF	OFF		
5 pulses / BAM 10									ON	OFF		
10 pulses / BAM 10									OFF	ON		
20 pulses / BAM 10									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

## V7P-BAM3(Pulse/ICT104V/ICT104U/MDB)

### Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
	BV1	BAM 10	BAM 10	BAM 10
BV2	BAM 20	BAM 20	BAM 20	BAM 20
BV3	BAM 50	BAM 50	BAM 50	BAM 50

### Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

### Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting