

V7P-GEL6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill GEL 5, 10, 20, 50, 100, 200 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject GEL 5 & 10	ON											
	Accept GEL 5 & 10	OFF											
★	Reject GEL 20		ON										
★	Accept GEL 20		OFF										
★	Reject GEL 50			ON									
★	Accept GEL 50			OFF									
★	Reject GEL 100				ON								
★	Accept GEL 100				OFF								
★	Reject GEL 200					ON							
★	Accept GEL 200					OFF							
	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / GEL 5								OFF	OFF			
	2 pulses / GEL 5								ON	OFF			
	5 pulses / GEL 5								OFF	ON			
	20 pulses / GEL 5								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7P-GEL6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	MDB	Pulse
BV1	GEL 5	GEL 5	GEL 5	GEL 5
BV2	GEL 10	GEL 10	GEL 10	GEL 10
BV3	GEL 20	GEL 20	GEL 20	GEL 20
BV4	GEL 50	GEL 50	GEL 50	GEL 50
BV5	GEL 100	GEL 100	GEL 100	GEL 100
BV6	GEL 200	GEL 200	GEL 200	GEL 200

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting