

V7P-HUF6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill HUF 500, 1000, 2000, 5000, 10000, 20000 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject HUF 500	ON											
★	Accept HUF 500	OFF											
★	Reject HUF 1000		ON										
★	Accept HUF 1000		OFF										
★	Reject HUF 2000			ON									
★	Accept HUF 2000			OFF									
★	Reject HUF 5000				ON								
★	Accept HUF 5000				OFF								
★	Reject HUF 10000 & 20000					ON							
★	Accept HUF 10000 & 20000					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / HUF 500								OFF	OFF			
★	5 pulses / HUF 500								ON	OFF			
★	10 pulses / HUF 500								OFF	ON			
★	20 pulses / HUF 500								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

- ◆ Note : 1.Default setting.
2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.
3.Remove the front cover and the dip-switch in on the CPU board.

V7P-HUF6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
Bill value				
BV1	HUF 500	HUF 500	HUF 500	HUF 500
BV2	HUF 1000	HUF 1000	HUF 1000	HUF 1000
BV3	HUF 2000	HUF 2000	HUF 2000	HUF 2000
BV4	HUF 5000	HUF 5000	HUF 5000	HUF 5000
BV5	HUF 10000	HUF 10000	HUF 10000	HUF 10000
BV6	HUF 20000	HUF 20000	HUF 20000	HUF 20000

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting