

V7P-MKD4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill MKD 10, 50, 100, 200 4bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MKD 10	ON											
	Accept MKD 10	OFF											
★	Reject MKD 50		ON										
	Accept MKD 50		OFF										
★	Reject MKD 100			ON									
	Accept MKD 100			OFF									
★	Reject MKD 200				ON								
	Accept MKD 200				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
	Pulse Mode												
★	1 pulse / MKD 10							OFF	OFF				
	5 pulses / MKD 10							ON	OFF				
	10 pulses / MKD 10							OFF	ON				
	25 pulses / MKD 10							ON	ON				
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note :

* Default setting

** Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

*** Remove the front cover and the dip-switch in on the CPU board.

V7P-MKD4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	MKD 10	MKD 10	MKD 10	MKD 10
BV2	MKD 50	MKD 50	MKD 50	MKD 50
BV3	MKD 100	MKD 100	MKD 100	MKD 100
BV4	MKD 200	MKD 200	MKD 200	MKD 200

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting