

V7P-MYR6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill MYR 1, 5, 10, 20, 50, 100 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MYR 1	ON											
★	Accept MYR 1	OFF											
★	Reject MYR 5		ON										
★	Accept MYR 5		OFF										
★	Reject MYR 10 & 20			ON									
★	Accept MYR 10 & 20			OFF									
★	Reject MYR 50				ON								
★	Accept MYR 50				OFF								
★	Reject MYR 100					ON							
★	Accept MYR 100					OFF							
★	Stack Banknote when Power-up					ON							
★	Reject Banknote when Power-up					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / MYR 1								OFF	OFF			
★	5 pulses / MYR 1								ON	OFF			
★	10 pulses / MYR 1								OFF	ON			
★	25 pulses / MYR 1								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063

V7P-MYR6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	MYR 1	MYR 1	MYR 1	MYR 1
BV2				
BV3	MYR 5	MYR 5	MYR 5	MYR 5
BV4	MYR 10	MYR 10	MYR 10	MYR 10
BV5	MYR 50	MYR 50	MYR 50	MYR 50
BV6	MYR 100	MYR 100	MYR 100	MYR 100
BV7	MYR 20	MYR 20	MYR 20	MYR 20

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100	ON			
	Decimal Point Position (DPP) = 2				
	Scaling Factor (SF) = 1	OFF			
	Decimal Point Position (DPP) = 0				
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Customized (Note.4)				ON
	Standard				OFF

★ Manufacture setting

Note : (4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063