

## V7P-NZD4

### V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill NZD 5, 10, 20, 50 4bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject NZD 5	ON											
★	Accept NZD 5	OFF											
★	Reject NZD 10		ON										
★	Accept NZD 10		OFF										
★	Reject NZD 20			ON									
★	Accept NZD 20			OFF									
★	Reject NZD 50			ON									
★	Accept NZD 50			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable				ON								
★	Harness Enable				OFF								
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / NZD 5								OFF	OFF			
★	5 pulses / NZD 5								ON	OFF			
★	10 pulses / NZD 5								OFF	ON			
★	25 pulses / NZD 5								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

## V7P-NZD4(Pulse/ICT104V/ICT104U/MDB)

### Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	NZD 5	NZD 5	NZD 5	NZD 5
BV2	NZD 10	NZD 10	NZD 10	NZD 10
BV3	NZD 20	NZD 20	NZD 20	NZD 20
BV4	NZD 50	NZD 50	NZD 50	NZD 50

### Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

### Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting