

V7P-THB4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill THB 20, 50, 100, 500 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject THB 20	ON											
★ Accept THB 20	OFF											
★ Reject THB 50		ON										
★ Accept THB 50		OFF										
★ Reject THB 100			ON									
★ Accept THB 100			OFF									
★ Reject THB 500				ON								
★ Accept THB 500				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / THB 10								OFF	OFF			
5 pulses / THB 10								ON	OFF			
10 pulses / THB 10								OFF	ON			
20 pulses / THB 10								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063

V7P-THB4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	MDB	Pulse
BV1	THB 20	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500	THB 500

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
Customized Mode (Note.4)				ON
★ Standard				OFF

★ Manufacture setting