

A6-GYD5

A6 Option Switch Settings: 1

Supported bill GYD 100, 500, 1000, 2000, 5000 5bills.

A6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject GYD 100	ON											
★ Accept GYD 100	OFF											
★ Reject GYD 500		ON										
★ Accept GYD 500		OFF										
★ Reject GYD 1000			ON									
★ Accept GYD 1000			OFF									
★ Reject GYD 2000				ON								
★ Accept GYD 2000				OFF								
★ Reject GYD 5000					ON							
★ Accept GYD 5000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / GYD 100									OFF	OFF		
★ 2 pulse / GYD 100									ON	OFF		
★ 5 pulse / GYD 100									OFF	ON		
★ 20 pulse / GYD 100									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Increase accepting rate will reduce its security level. Use this option carefully!

A6-GYD5(Pulse/ICT002)

A6 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002 Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

A6 Interface Settings: 2 (ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	GYD 100	GYD 100
BV2	GYD 500	GYD 500
BV3	GYD 1000	GYD 1000
BV4	GYD 2000	GYD 2000
BV5	GYD 5000	GYD 5000