

A7/V7-KWD4

A7/V7 Option Switch Settings (Pulse/ICT106) Supported bill KWD 0.25, 0.5, 1, 5 4bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject KWD 0.25	ON											
	Accept KWD 0.25	OFF											
★	Reject KWD 0.5		ON										
	Accept KWD 0.5		OFF										
★	Reject KWD 1			ON									
	Accept KWD 1			OFF									
★	Reject KWD 5				ON								
	Accept KWD 5				OFF								
★	Reserved				ON								
	Reserved				OFF								
★	High Acceptance					ON							
	High Security					OFF							
★	Harness disable						ON						
	Harness enable						OFF						
★	Inhibit Active High							ON					
	Inhibit Active Low							OFF					
★	1 pulse / KWD 0.25								OFF	OFF			
	2 pulse / KWD 0.25								ON	OFF			
	4 pulse / KWD 0.25								OFF	ON			
	20 pulse / KWD 0.25								ON	ON			
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		100ms on / 100ms off								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-KWD4(Pulse/ICT106)

A7/V7 Interface Settings: 2

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT106 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	KWD 0.25	KWD 0.25
BV2	KWD 0.5	KWD 0.5
BV3	KWD 1	KWD 1
BV4	KWD 5	KWD 5