

A7/V7-KZT3

A7/V7 Option Switch Settings : 1

Supported bill KZT 200, 500, 1000 3bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject KZT 200	ON											
★	Accept KZT 200	OFF											
	Reject KZT 500		ON										
★	Accept KZT 500		OFF										
	Reject KZT 1000			ON									
★	Accept KZT 1000			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / KZT 100									OFF	OFF		
	2 pulse / KZT 100									ON	OFF		
	4 pulse / KZT 100									OFF	ON		
	20 pulse / KZT 100									ON	ON		
★	Pulse Speed	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-KZT3(Pulse/MDB)

A7/V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 Interface		OFF		
	Reserved			ON	
★				OFF	
					ON
★					OFF

★ Manufacture setting

A7/V7 Interface Settings: 2 (RS232)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
	Reserved			ON	
★				OFF	
					ON
★					OFF

★ Manufacture setting

V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface (Note 1)		OFF		
	Reserved			ON	
★				OFF	
					ON
★					OFF

★ Manufacture setting

Note: (1) Please refer to the dip-switch #1 of internal dip-switch for MDB Decimal Point Setup.

V7 Interface Settings: 2 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface (Note 1)		OFF		
	Reserved			ON	
★				OFF	
					ON
★					OFF

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	KZT 200	KZT 200
BV2	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000